

This Information Is Provided By
CBTricks.com

How to install the Powerband RFX75
on Uniden 68 series radios.

Liability of damages to any equipment is the sole responsibility of the user!
Downloading, viewing, or using any information provided on these pages
automatically accepts the user to the terms of this agreement!
Modifications are provided for information purposes only!
Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

The site is supported with donations from users, friends and selling of the Site Supporters DVD's to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

All the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the eBay CB sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.
This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

Thank you for any support you can give.


For information on how to Support CBTricks.com
<http://www.cbtricks.com/support/>

The user is solely responsible for making sure that any modifications made to the radio unit must meet all Federal and State Regulations or the Country of use! Liability of damages to any equipment is the sole responsibility of the user! Downloading, viewing, or using any information provided on these pages automatically accepts the user to the terms of this agreement! Modifications are provided for information purposes only! Disclaimer: CBTricks.com does not warrant the accuracy of the information contained herein nor is it responsible for any errors or omissions and assumes no liability for the content on this site. While CBTricks.com uses reasonable efforts to include accurate and up to date information, CBTricks.com makes no warranties or representations as to its accuracy or timeliness and assumes no liability or responsibility for any errors or omissions in the content of this site.


RFX75 – Uniden 68 Installation

1. On the solder side of the radio PCB, remove the 33pF capacitor that is soldered across the final transistor leads.
2. Remove D8, R40, and the final transistor from the Uniden 68.
3. Locate the wire soldered from the antenna connector to the circuit board of the radio. Unsolder this wire from the circuit board – leave the other end of the wire soldered to the antenna connector.
4. Replace R53 with a 470K ohm resistor. R53 is located near the audio amp IC.
5. Remove the 22pF capacitor at C1 and keep it for the next step.
6. Solder one lead of 22pF capacitor to the unsoldered end of antenna connector wire. Connect the other lead of 22pF capacitor to cathode (stripe) side of D1. *This reconnects the RX circuit of the radio to the antenna connector.*
7. Cut and remove the BLUE wire from the RFX75.
8. Cut and remove the RX OUT coaxial cable from the RFX75.
9. Drill and mount the RFX75 to the rear panel of the radio.
10. Solder the ORANGE wire from the RFX75 to the cathode side of D10. Do not remove D10.
11. Solder the YELLOW wire from the RFX75 to the cathode side hole of D8.
12. Solder the RF OUT coaxial cable center conductor to the center of the antenna connector. Solder the shield to the antenna connector tab (chassis ground).
13. On the solder side of the board (with the front panel of the radio facing you), solder the RF IN coaxial cable center conductor to the right most trace from where the final transistor was removed. Solder the shield to DC ground.
14. Solder the RED and BLACK wires from the RFX75 to the back of the radio's power jack – observe polarity!
15. After tuning the radio, verify that the carrier is not higher than 15 watts. If the carrier is higher than 15 watts, perform the following steps.
 - a. Remove JV17 and install a 1000 μ F, 16 volt electrolytic capacitor with the negative lead of the capacitor towards the back of the radio.
 - b. On the back of the PCB, Install a 10ohm to 33ohm resistor across the two points of JV17 to obtain the desired carrier level. Typically, a 15 ohm resistor is about right.
16. If the carrier is lower than the desired amount, you can add a 68pF ceramic disc capacitor across C46. This will increase the carrier slightly.

The user is solely responsible for making sure that any modifications made to the radio unit must meet all Federal and State Regulations or the Country of use! Liability of damages to any equipment is the sole responsibility of the user! Downloading, viewing, or using any information provided on these pages automatically accepts the user to the terms of this agreement! Modifications are provided for information purposes only! Disclaimer: CBTricks.com does not warrant the accuracy of the information contained herein nor is it responsible for any errors or omissions and assumes no liability for the content on this site. While CBTricks.com uses reasonable efforts to include accurate and up to date information, CBTricks.com makes no warranties or representations as to its accuracy or timeliness and assumes no liability or responsibility for any errors or omissions in the content of this site.



The user is solely responsible for making sure that any modifications made to the radio unit must meet all Federal and State Regulations or the Country of use! Liability of damages to any equipment is the sole responsibility of the user! Downloading, viewing, or using any information provided on these pages automatically accepts the user to the terms of this agreement! Modifications are provided for information purposes only! Disclaimer: CBTricks.com does not warrant the accuracy of the information contained herein nor is it responsible for any errors or omissions and assumes no liability for the content on this site. While CBTricks.com uses reasonable efforts to include accurate and up to date information, CBTricks.com makes no warranties or representations as to its accuracy or timeliness and assumes no liability or responsibility for any errors or omissions in the content of this site.



The user is solely responsible for making sure that any modifications made to the radio unit must meet all Federal and State Regulations or the Country of use! Liability of damages to any equipment is the sole responsibility of the user! Downloading, viewing, or using any information provided on these pages automatically accepts the user to the terms of this agreement! Modifications are provided for information purposes only! Disclaimer: CBTricks.com does not warrant the accuracy of the information contained herein nor is it responsible for any errors or omissions and assumes no liability for the content on this site. While CBTricks.com uses reasonable efforts to include accurate and up to date information, CBTricks.com makes no warranties or representations as to its accuracy or timeliness and assumes no liability or responsibility for any errors or omissions in the content of this site.