

COBRA 29GTL

VR4: Adjust for 100% modulation

COBRA 47XLR

Adjust L109 for maximum RF power

VR 105: Adjust for 100% modulation

VR 104: RF meter adjustment

Connect pin 11 of IC101(MB8719) to pin 9

COBRA 86XLR

Adjust L6 and L3 for maximum RF power

R4: RF meter adjustment

R17: S meter adjustment

Take pin 8 low by cutting print and adding a
4.7k resistor across cut. Add a switch, one side to ground,
other side to pin 8 of IC10.

COBRA 132XLR

Adjust L7 and L3 for maximum RF power

R134: Adjust for 100% modulation

R9 : RF meter adjustment

R130: SSB automatic level control
maximum adjustment

R93 : modulation meter adjustment

Connect pins 7 and 8 of IC304 together for
more frequencies.

COBRA 135XLR

Adjust L7 and L3 for maximum power

Adjust T7 for maximum RF output on SSB

R130: Adjust for maximum power SSB
automatic level control

R134: Adjust for 100% modulation

R9 : RF panel meter adjustment

✓CLARION DMA066, JC202E, RCJ003

Adjust L205, L204, L203, L201 for maximum
power

VR201: Adjust for 100% modulation