

SPECIFIC RADIO TUNE-UPS

AUDIOVOX MDU 6000

Adjust L202 for maximum RF power output channel 19
R279: Adjust for maximum modulation
R281: Modulation 50% set so all led's are on
R257: Squelch range adjustment
R236: S level indication adjust

CHANNEL MASTER CB6835

VR6: Adjust for maximum modulation
VR7: RFPO meter adjustment
VR1: AGC adjust
VR3: SQ range
VR4: S Meter
VR10: RF gain range adjust
Adjust L905 for maximum RFPO on channel 19

CHRYSLER MODELS 4048076/8077 AM/FM CB

Adjust VR251, 252 for maximum modulation
VR201: RF power meter adjust
VR302: AGC
VR303: SQ range
VR301: S meter
VR305: Audio gain

CLARION TC-203E

Adjust: L203 for maximum RF power output on channel 19
Adjust: VR201 for maximum modulation on chip D205

COBRA 89GTL, 1000GTL

VR6: Adjust power maximum modulation
VR5: Modulation meter adjust
VR4: RF power meter adjust
VR1: IF gain adjust
VR3: Squelch range adjust
VR2: S meter
Adjust L13 for maximum RF output on channel 19